

AMT 16

Motor : Mitsubishi
Alternatör : Stamford
Kontrol Sistemi : P 602



ISO8528

6i 'YbYfUht f [fi Vi '-GC,) & , 'm bYra Y'] UfhUfibi' _Uf i'UntUWU_ 'gYj]nYXY 'hUgUfUba i' hif"

SZUTEST

6i 'YbYfUht f [fi Vi '-GC - \$\$\$gYfhZ_U" nY']_Yf]bY [" fY 'hUgUfUba i' j Y' fY]a] hif"



6i 'YbYfUht f [fi Vi '79'gYfhZ_U' UfhUfibiU'i m] i bXi f

2000/14/EC

GYG'mUihä '_UV]b' [fi d'Ufz&\$\$\$#/(#7 '5j fi dU [' f 'h' m bYra Y'] bY [" fY 'hYghYX]]f"

u]] ; 'WZ' !: Uniz) \$<nz; : '\$z

Voltaj	Standby Güç (ESP)		Prime Güç (PRP)		
	kVA	kW	kVA	kW	Amp
400/230	16,00	12,80	14,50	11,60	20,00

Standby Güç (ESP): ; 'jYb]f' YVY'_UnbU 'ibib'_Yg]a Yg]Xi fi a i bXUZXY]_YbYY_hf_]m_Y [' , 'Ya]b_Yra YXY'_i 'Ubrif''9GDz'-GC,) & , 'Yi m a i Xi f''5 ifi m_Ya YnY']n]b] Yf]a Ya] hif"

Prime Güç (PRP): 8Y]_YbYY_hf_]m_Yz [' , 'Ya]b_Yra YXYZm'_gibifgin', U' a U gUUh]]_b] 'Ubrif''DF DZ'-GC,) & , 'Yi m a i Xi f''-GC' \$(* mU [' fY '%&gUUh, U' a U dYf]ncXi bXU%gUUh%\$& ' U' ifi m_Ya Y]]_b] 'Ubrif''

GH5B85F H'x N9@@? @9F

Gi 'gc i ha U'X]nY'a ctef
FUXntUht f'j Ya Y_Ub]_ZUb
8" bYb j Y'giWU_dUF, UUFU'Xc_j ba Um'i" b'YnYb_cfi m' W'_UZyg
9'Y_hf_]a Uf 'a ctefi j Y' UF^U'YfUht f'
5'_f] f i b Ug]h]z'_UV'c'Ufij Y'gY\ dUg
A ctef V'c_gi m' igihWgi
uY]_ UgY j Y'hfY 'a " b'YnY'YfU_cn'Uf' UgYnY YbY [fY nU_ih]U_b_j
9gbY_nU_ihVU 'Ubh'cffi a 'Ufi
HY_nU_ih]z j Y < nU'ihä 'gibiZi U'YfUht f'
9bX' gh]nY'_UdUg]YXY'gi gh fi W j Y.YgbY_]_]_ca dYbgUht f'
9'Y_hfcb]_U'_ UF^V\Uht
? i 'Uba U j Y a cblU^_Uj i ni

>9B9F 5Hx F '8CB5B-A 'G9u9B9? @9F

MOTOR
! 'i nU_fUXntUht f' 'gc i ha U

YARDIMCI DONATILAR
! C'ca U]] YnU'a Ubi Y' nU_ihXci a 'g]hYa]
! MU 'Vc U'ha UzY'dca dUg
- Egzoz susturucusu, meskûn mahal tip
! A i \Uz]nU'_UV]b] /gYg nU'ihä 'i'h]d j YnU'U, i'_U'Ub'h]d
- Römorklar
! 5'YhU_ia i'fVU_ia]]_b
! 5bU'MU_ih]U_b_j

ALTERNATÖR
! 'u]] ' U'Yf]

KONTROL PANOSU
! ' UF^Ua dYfa YfYg]

TRANSFER PANOSU
- Üç veya dört kutuplu transfer sistemi
! 'y, j YnU'X' fh] h d' i a ctefi ; i] ' U'Yf]

AMT 16

Motor : Mitsubishi
Alternatör : Stamford
Kontrol Sistemi : P 602

8 N9@A C H C F 'x N9@@? @9F

Üretici		Mitsubishi
Model		S4L2
G]j]bX]f]j Y' HUgUfia		('G]j]bX]f]j'Z GifU'i'H]d
Hava Emme		8c U'9a]]
Maksimum Standby Güç		1500 d/dk
		15,40 kW [20,70HP]
Toplam Silindir Hacmi	L	1,758
Çap ve Strok	mm	78 x 92
G]i] hifa U'C fUbi		22:1
Norminal Devir	d/dk	1500
Governör Tipi		Mekanik
MU' ? UdUg]Yg]	L	6,00
Su Kapasitesi	L	7,75
Elektrik Sistemi		12 V d.c.
MU_ihH' _Y]a]	Yük	%100
	L/sa	4,90

5@H9F B5Hx F 'x N9@@? @9F

Üretici		Stamford
Modeli		PI 044G
Frekans	Hz	50
Güç	kVA	15,00
HUgUfia		: if, Uginz(' _i h d'i
Cos fi		0,80
: Un'GUmigi		3
Voltaj	V	400/230
5_ia	A	21,00
MU'iha GibiZ		H
Stator		&#' UXia
Rotor		u]ZiMUU_ i'9gbY_ '8]g_]
_Un'G]g]Ya]		Elektronik (AVR)

6CM H'j Y'5 ₺ @?

5, i_ ; fi d	?i fi '5 ifi_	Boy	En	Yükseklik	MU_ih8Ydc ? UdUg]Yg]
	kg.	mm.	mm.	mm.	L
AMT 16	405,00	1360,00	850,00	950,00	50,00
Kabinli Grup	?i fi '5 ifi_	Boy	En	Yükseklik	MU_ih8Ydc ? UdUg]Yg]
	kg.	mm.	mm.	mm.	L
AK 10	585.00	1850	860	1060	50

AMT 16

Motor : Mitsubishi
Alternatör : Stamford
Kontrol Sistemi : P 602

1 P 602 - Kontrol Sistemi



- 1 ; YbYXi fi a j Y", a Y V][]Yf][" ghYf[Y_Y_fUbi"
- 2 9_fUb V][]Yf][]YfYfa Y Vi hcbi "
- 3 GUnZU Vi hcbi "
- 4 C fU_U'Ufa i[" ghYf[Yg]"
- 5 8i fi a '@98 fYf]"
- 6 uU'i a U' Y_]gY, a Y'Vi hcb'Ufi"

2 Cihazlar

8G9za cXY**\$&\$'chca UH_ YVY_Y'UfinU'nYa Y j Y'YbYfUf f_cbfcc'a cX""
9_Y_fcb]_U_' UF'V\Uni;]f] '%, !&* (j c'hZu'i_i '&+* j) '5'f&(j k j YntU'% ž j c'h) 5'f&U k
5WY'Xi fXi fa U'Vi hcbi j Y_cbfcc'XYj fY'Yf]], j'g][cffU'Uf"

3 Müdi'j Y'6cnu

7\Un'Uf, Y_L'gUWU'ja U'YX]a] 'dUbc_'UV]b]bY'a cbfU'^ntüdi'if"DUbc'gUWZc'gZU'h_]a ntUgU'i]Y'_Ud'UbfU'_gUW
m'nYm'_cfcnc'cbU'X]fYb,]\UY'[Yhf]f]"Dc'mYghYfV]Y]_hcn'VcnU'j Y Zfib'Ua U] 'Ya]]Y'dUbc_'UV]b]bY'gcb'XYfYW
XUnübi_'i'VcnU'ntüdi'if?]h]] Y'a YbY' Y]dUbc_'UdU 'i]Y'V\Un'UfU'i 'U' a U_'c'UnXif"

4 Montaj

?cbfcc'dUbcgi ž YbYfUf f[fi Vi ' Ug]g]' nYf]bXY_], Y_L'UnU_'Uf]Y'VU 'Uba i' hif"DUbcž'YbYfUf f[fi Vi bi b'gU'ntü
kUfUZbU'f[fi VU'U'YfbU'cf'kUfUZbXUb-VU_ibVW'knYfY 'hf]a] hf"

5 Jeneratör Kontrol Ünitesi

&\$\$_j 5'XU\]j Y_', _[_[, XY_]YbYfUf f[fi d'Ufia inXU'8G9*\$&\$'_cbfcc'a cX""'ghU'XU'fXif"A cX""ž[Unj Y'X]nY'
a chcfi 'YbYfUf f[fi d'Ufib'chca UH_'c'UfU_', U'i hifa Ugi j Y'Xi fxi fi 'a Ugibi'[Yf, Y_Y' hf]f]"A cX""ž'YbYfUf f' b
ZY_Ubgjž] c'kU'žU_ia iža chcf'ntü 'VUgibVžgc i ha U'gi m'giVW_'i ž, U'i a U'gU'UžU_' j c'kU'fbi]n'YnYVW_] Y '@8
Y_fUbXU[" ghYfYVW_' Y_]XY'kUgU'fUba i' hif"5mfiVW'a cX"" YVY_Y'j c'kU'fbi] Y ZY_Ubgibi]n'Yf] Y'mXY_'YbYfUf f
[fi Vi]Y'cbU'VU 'i[, hfUbgZY'f]g]hYa]b]_cbfcc'YXYf">YbYfUf fXY'UfinU'a YnXU'U' [Y'X]]bXY'chca UH_'c'UfU_
YbYfUf f'Xi fxi fi i' f j Y]]'UfinU'a cX"" b"" b'dUby']bXY '@8 Y_fUbXU[" ghYf]f]"

Standart Özellikler

- A]_fc] 'Ya WY]Y'_cbfcc"
- @78 Y_fUbXUbžV][]Yf]_c'Umc_i a U"
- (! gifUž*(' % &[fUZ_ Y_fUb"
- YVY_Y'j Y'YbYfUf f[, Yf]U'fUgibXU'fU'Zyf'_cbfcc""
- x b'dUby' nYf]bXYb'a Ub'Y'dfc[fUa 'Ua U"
- 6i hcb'Ufib'nYfY 'ja] j Y] 'Yfa Y'g]hYa]_c'Um'
- x b'dUby'XYb'dfc[fUa 'Ua U"
- I nU_fUb; U'i hifa U"
- <UZnUnU'_Umih'i) 'U'Ufa i[" fYV]a Y"
- ?cbfcc'h 'Ufi. G'hd#GizfZA Ub' Y'žC'ha UH_žHYgržG'UfžVi hcb'Ufi""@78 Y_fUb V][]g]b]]YfYfa Y'hi i "

AMT 16

Motor : Mitsubishi
Alternatör : Stamford
Kontrol Sistemi : P 602

Ölçme Göstergeleri

A C H C F
A c h c f X Y j f j"
M U ` V U g i b W"
G i ` g i V U _ i i "
u U i ` a U ` g U U j "
5 _ j c ` t U t "
5 n t U f U b U V] j f n U a U b ` U a U "
> 9 B 9 F 5 H x F
J c ` t U ` f @ @ z @ B E "
5 _ j a ` U f ` f @ @ z @ B E "
: f Y _ U b g "
9 6 9 ? 9
J c ` t U > f @ @ z @ B E "
: f Y _ U b g "
Y V Y _ Y < U n i f "
Y V Y _ Y 8 Y j f Y X Y "
> Y b Y f U h f < U n i f "
> Y b Y f U h f 8 Y j f Y X Y "

Koruma Devreleri

? 5 N
U f ` U Y f b U h f U f i n U g i "
8 ` _ # M _ g Y _ U _ j c ` t U t "
G h c d ` U f i n U g i "
8 ` _ # M _ g Y _ Y b Y f U h f j c ` t U t "
8 ` _ # M _ g Y _ Y b Y f U h f Z Y _ U b g i "
8 ` _ # M _ g Y _ a c h c f ` \ i n i "
8 ` _ n U ` V U g i b W "
M _ g Y _ g i ` g i V U _ i i "
8 I F 8 I F A 5 ` 5 @ 5 F A @ 5 F =
G h U f i U f i n U g i "
5 V j ` g h c d "
8 ` _ n U ` V U g i b W "
M _ g Y _ g i ` g i V U _ i i "
8 ` _ # M _ g Y _ a c h c f ` \ i n i "
8 ` _ # M _ g Y _ Y b Y f U h f Z Y _ U b g i "
8 ` _ # M _ g Y _ Y b Y f U h f j c ` t U t "
M U ` V U g i b , a _ j f j V U ` U b h g i ` n e _ "
< U f U f Y h a _ j f j V U ` U b h g i ` n e _ "
9 @ 9 ? H F G 9 @ 5 u A 5
> Y b Y f U h f U i f i U _ j a "

Opsiyon Özellikleri

< U f j W j g Y b g ` f j Y ` V U g i b , z j i V U _ i _ z m n X Y g Y ` _ c b f c `
j a _ U b i f i n t U f i z _ U d U h a U j Y ` Y ` Y _ j f j _ g Y ` U f i n U t "
D 7 f X Y b ` I G 6 _ U V c ` j Y ` a c X ` _ b ` c _ U ` c ` U f U _
d f c [f U a ` U b a U g i j Y ` j n Y b Y V] a Y g j f a U _ g ` ` a Y h Y k "

Standartlar

9 ` Y _ Y _ h f j _ g Y ` ; _ j Y b _ j # 9 A 7 i m i b i _ ` 6 G ` 9 B ` * \$ -) \$
9 ` Y _ h f j _ j] ` V U ` U n ` U f i "
6 G ` 9 B ` * \$ \$ \$! * ! & 9 A 7 ` a i U z j n Y h g h U b X U f i "
6 G ` 9 B ` * \$ \$ \$! * ! (` 9 A 7 ` Y a j g n e b g h U b X U f i "

9 ` Y _ h f c b _ j _ 5 _ ` U f ` 7 j \ U n i

5 _ ` U f ` V U ` U n i g k j W X j b [! a c X Y j Y G A 8 ` h Y _ b c ` c j g] j Y ` f Y h ` a] X j f j Y m _ g Y _ j Y f j a Y ` g U \ d h j f 5 _ ` z j ! ` = _ U f U _ h y f j g h _
Y ` f j g j b Y [" f Y ` U f ` Y X j] f ") ` U a d Y f z % z j c ` h f W & j Y ` & + z ` j c ` h f & (j k " ; j f j ` % , ! * (j c ` h 5 7 " 7 j \ U n , i _ i _ i g U ` X Y j f Y n Y
_ U f _ i _ c f i b a i h f " D f c j b Y % & \$) # & (\$) : U f ` V U ` U n i z ` j b Y Y f : U f ` V U ` U n i f i b U [" f Y ` X U \ U j Y f j a ` j z i n i b " a ` f ` z U f i n U ` c f U b i X U \ U
X ` _ z \ U z j j Y t g i n U n a U g i , c _ X ` _ _ h f " U f ` U f i n U g i , i _ i ` i a Y j W h i f " F : = z j h Y j Y ` a U b n Y h _ d U f U n j h y f j V U g h f a U " n Y " j "
; U j U b _ j n c Y j [j f j Y , i _ i ` U f i (_ j f U _ U X U f U h U a U U f U X U n U b i _ i X i f "

AMT 16

Motor : Mitsubishi
Alternatör : Stamford
Kontrol Sistemi : P 602

AK 10 - Kabin



- 1 uY_L'gUWUbnüdi
- 2 Acil durdurma butonu
- 3 ? cbfrc'dUbcgi 'gU 'HUFUZU' UgYnY'a cbHU'YXif
- 4 ? cfcncnbU'XUnübi_'i_]hj Y'a YbY' Y'Yf
- 5 MU 'Vc U'ha U'\Uhi'a cfcf' nYf]bXY j UbU]Y
- 6 GYg'nüiha 'a UnYa Y'Yf]
- 7 8Ydc! UgY

yf' b'<U_übXU

GYg'MU'ihä 'ij Y' cfi mi W' ? UV]bYf'5_gU'YbYfUH f [fi d'Ufi'],]b'U_i gh'_a '\YbX]gYf] 'HUFUZbXUbžncf\Uj Uj Y', Yj fy UfhUfibU'i m[i b' [Y] Hf]Yb'gYg'nüihä 'iz_cfi a U'_UV]bYf] / [XYU'gYg'gY]]nYg] j Y'_cfi a U'gU 'UnüWU'_' Y_]XY 'HUGUF'Ubi'Uf' 5_gU'_UV]bYf]ždUf, U'dUf, U'g'_'YV]]fa cX'Yf'nüdiXUž [fi VU'_c'Umgyfj]g] Y'VU'_ja 'nüdUV]a Y j Y', U'i hi' 'imYfXY'dUf, U XY]]a]bY'c'UbU_gU 'Uf'5nbi'nüa UbXU'YbYfUH f [fi Vi bi b'; Yj fy'giWU'_i'ibU' [" fy'gc' i'ha U'dYfZcfa Ubgi'j Y [' , '] XY Yf]bXY'\Yf'Ub []gY]]nY'X' ' - ' - 'a YnXUbU' [Y]hfa YnYW'_nüdiXU'c'a UgibU'X]_U'YX]Yfy'_UV]bYf'X]nUmb'YX]a] X]f' ? UV]bYf]b'; Yj fy'giWU'_i'ij Y'gYg'gY]]nYg] i m[i b' i],]b'dfcU]hd'YghYf]nüdi'Xi'_HUb'gcbfU' fy]ha]nüdi'a i'hi'

Standart Özellikler

8' ' _dfcZ'] j Y'_Ud'Ua U'U'Ubi'Unžf]ca dU'_H'UgUfia
? UV]bž'YbYfUH f gYhžY [ncn'g]ghYa] j Y'nü_ihXYdcgi ž' Ug] 'Y' _dU'Yhc'UfU'_gY] _'YX]YW'_' Y_]XYžV]fV]f]b]V' hi b'YnYW'_' j Y'_c'Uma cbHU'],]b' [Y] Hf]a] Hf'
?]a nUgU'HYa]nYa Y] 'Ya]bXYb [Y,]f]Ybž'_UV]b'; Y'_gUWdUf, U'Ufiždc'nYgHYf'hc'n'VcnU'U'_Ud'Ubif] j Y'žfif'Ubif 5'Yj "' b'YnY'W'nüihä 'g' b [Yf]
GYfj]g'bc'_H'UfibU'_c'UmYf]]a
? UV]b], Yf]g]bXY Y [ncn'g]ghYa] j Y'igi'nüihä i '_HUFUZU' [Yb] '_Udi'Uf
?]h]'_'Udi' nYf]bXY' YZUZdYbW'fYXYb'_cbfrc'dUbcgi bi]n'YnYV]a Y
? UV]b]b'Xi' ibU'a cbHU'Y'UVY'ghcd'Vi hcbi
Gc' i'ha U'Zb]i'j Y' Uf'U'Yf'U'f' f' 'Xc'_i'ba Unü'_Uf' i'_cfi'ba i' hi' f
?]hYbYb'_Udi']Y'nü_ihXc' i' a i' j Y'U'_'mY'Yf]]a
Ug]j Y'_UV]b' nYf]bXY'_U'Xifa U'bc'_H'U'Ufi
GYg'nüihä '_UV]b' [fi d'Ufi'bgYg'HYgh] &\$\$#&/ (#7' mY' i n[i b'c'UfU'_Gni'HYgh]U'FUZbXUb'XYbYhYba Y'_HYX]f'

En	mm.	860
Boy	mm.	1850
Yükseklik	mm.	1060
MU_ihHUb_'? UdUg]HYg]	L	50