



## GJM Serisi Dizel Jeneratör Seti Özellikleri

MODEL		GJM870	GJM1007	GJM1109	GJM1257	GJM1815	GJM1840	GJM2038	GJM2291	GJM2544	GJM2800	GJM3112	GJM3305		
JENERATÖR	GÜCÜ Güç Faktörü 0.8	STAND BY	kVA	870	1007	1109	1257	1815	1840	2038	2291	2544	2800	3112	3305
			kW	696	805	887	1005	1452	1472	1630	1832	2035	2240	2489	2644
	PRIME	kVA	787	912	1008	1138	1650	1653	1828	2090	2279	2543	2811	2992	
		kW	629	729	806	910	1320	1322	1462	1672	1823	2034	2248	2393	
MARKA		MTU													
MODEL		12V2000G65/G85 16V2000G25/G45 16V2000G65/G85 18V2000G65/G85 12V4000G23/G43 12V4000G23/G43 12V4000G63/G83 16V4000G23/G43 16V4000G63/G83 20V4000G23/G43 20V4000G63/G83 20V4000G63/G83													
TİPİ		DİREK ENJEKSİYONLU													
GÜCÜ, 1500 D/D		kWm	765	890	975	1100	1575	1575	1750	1965	2185	2420	2670	2850	
SİLİNDİR HACMİ		Litre	12 V	16 V	16 V	18 V	12 V	12 V	12 V	16 V	16 V	20 V	20 V	20 V	
ASPIRASYON VE SOĞUTMA		TURBO ŞARJLI - INTERCOOLER													
MOTOR DEVRİ		1500													
BORE VE STROKE		mm x mm	130 x 150	135 x 150	130 x 150	130 x 150	170 x 210	170 x 210	170 x 210	170 x 210	170 x 210	170 x 210	170 x 210	170 x 210	
SIKIŞTIRMA ORANI			16:1	16:1	16:1	16:1	16,5:1	16,5:1	16,5:1	16,5:1	16,5:1	16,5:1	16,5:1	16,5:1	
GOVERNÖR SINIFI		ELEKTRONİK													
TAM YÜKTE YAKIT SARFIYATI		g / kw x h	202	196	195	200	194	194	194	195	193	199	196	195	
YAKIT TANKI KAPASİTESİ		Litre	1500	1500	1500	2000	2500	2500	3000	3500	3500	4000	4500	4500	
YAĞ KAPASİTESİ		Litre	77	102	102	130	260	260	260	300	300	390	390	390	
AĞIRLIĞI		Kg	5750	6650	6700	7400	11000	12000	12500	14000	14500	17000	17500	18000	
MARKASI		MARANELLO													
ÇIKIŞ GERİLİMİ		Hz.	230/400												
FREKANS			50												
OTOMATİK VOLTAJ REGÜLASYONU		cm.	±% 0,2												